

# Surveillance Two Wire Earpiece with Acoustic Tube

> 11ACH2042



## Features

- > Surgical grade acoustic tube; discreet and comfortable
- > Quick-fasten secure structure
- > Environmental PU cable reinforced with Kevlar
- > Optional ear mold allows ambient sounds
- > Discreet communication in sensitive environments
- > Suitable for many applications including; security personnel, hotel and catering staff, etc

## Technical Specification

### Speaker

|                       |                        |
|-----------------------|------------------------|
| Dimensions:           | $\Phi$ 16.2mm * 10.6mm |
| Impedance:            | 250 $\pm$ 500hm        |
| Sound Pressure Level: | 104 $\pm$ 3db @1000Hz  |

### Microphone

|                    |  |
|--------------------|--|
| Type:              | Electric Condenser Microphone          |
| Impedance:         | 2.2 kOhm                               |
| Sensitivity:       | -40 $\pm$ 3db @1000Hz<br>(0db = 1V/PA) |
| Operating Voltage: | 11.1-10VDC                             |

### PTT

|             |                      |
|-------------|----------------------|
| Dimensions: | 34.9 * 14.2 * 11.8mm |
|-------------|----------------------|

Call us now to find out more **0121 552 0067**  
or email the sales team: [shopbleeperltd@aol.com](mailto:shopbleeperltd@aol.com)

T/as Universal Radio Hire and Sales

Bleeper Services Ltd

Unit 6, Birch Court, Sandwell Business Park  
SMETHWICK, West Midlands, B66 1RB

T: 0121 552 0067

E: [shopbleeperltd@aol.com](mailto:shopbleeperltd@aol.com)

## > Connectors

|   | Product Code         | Description   |
|---|----------------------|---|
|    | 11ACH2042 <b>M2</b>  | Surveillance two-wire earpiece with acoustic tube with <b>Motorola two pin 2.5mm for T5</b> . Suitable for Motorola T5 series   |
|    | 11ACH2042 <b>M1</b>  | Surveillance two-wire earpiece with acoustic tube with <b>Motorola Two-pin right angle</b> . Suitable for Motorola: GP300, CP040, XTN446, HYT: TC600, TC610/TC620, TC446  |
|    | 11ACH2042 <b>M1A</b> | Surveillance two-wire earpiece with acoustic tube with <b>Motorola Two-pin right angle</b> . Suitable for Motorola: XTNi and XTNiD  |
|    | 11ACH2042 <b>M4</b>  | Surveillance two-wire earpiece with acoustic tube with <b>Motorola multiple pin M4</b> . Suitable for Motorola: GP328, GP340, GP360, GP380  |
|    | 11ACH2042 <b>M5</b>  | Surveillance two-wire earpiece with acoustic tube with <b>Motorola multiple pin M5</b> . Suitable for Motorola: GP344, HYT: TC-780, TC3000 Kirisun: PT7200  |
|    | 11ACH2042 <b>M7</b>  | Surveillance two-wire earpiece with acoustic tube with <b>MOTOTRBO multiple pin</b> . Suitable for Motorola: DP3400/DP3600  |
|   | 11ACH2042 <b>K1</b>  | Surveillance two-wire earpiece with acoustic tube with <b>Kenwood two-pin</b> . Suitable for Kenwood: TK-2100, 2102, 2130, 2160, TK-3100, 3160, TK-3101, TK-3102, TK-3130   |
|  | 11ACH2042 <b>K2</b>  | Surveillance two-wire earpiece with acoustic tube with <b>Kenwood Multiple pin</b> . Suitable for Kenwood: TK-280, TK-290, TK-380, TK-385, TK-390, TK-480, TK-481, TK-2041, TK-2140, TK-3140, TK-3148   |
|  | 11ACH2042 <b>S2</b>  | Surveillance two-wire earpiece with acoustic tube with <b>Icom two pin right angle</b> . Suitable for Icom: IC-F3G, IC-F3GS, IC-G3GT, IC-F4G, IC-F4GS, ICF4GT, IC-F43GS, IC-F43GT, IC-F43TR, IC-F11, IC-F11S, IC-F21, IC-F21S, IC-F31           |
|  | 11ACH2042 <b>S4</b>  | Surveillance two-wire earpiece with acoustic tube with <b>Icom multiple pin</b> . Suitable for Icom: IC-F50, IC-F51, IC-F60, IC-F61, IC-F30GS, IC-F3061, IC-F4061, IC-F3162, IC-F4162   |
|  | 11ACH2042 <b>Y2</b>  | Surveillance two-wire earpiece with acoustic tube with <b>Yaesu/Vertex Standard One-Pin Right Angle with screw</b> . Suitable for Vertex: VX-10, VX-110, VX-160, VX-180, VX-210, VX-210A, VX-200, VX-300, VX-400, VX-410, VX-420, VX-150, VX-2R |
|  | 11ACH2042 <b>Y6</b>  | Surveillance two-wire earpiece with acoustic tube with <b>Yaesu/Vertex Standard Multiple-Pin</b> . Suitable for Vertex: VX-820, VX-82, VX-824, VX-829, VX-920, VX-921, VX-924, VX-929   |
| No image available  | 11ACH2042 <b>ET1</b> | Surveillance two-wire earpiece with acoustic tube with Entel. <b>Suitable for Entel HX series:</b> HX402/403/405, 412/413/415, 422/423/425, 482/483/485   |
|  | 11ACH2042 <b>T1</b>  | Surveillance two-wire earpiece with acoustic tube with Tait. <b>Suitable for Tait:</b> TP8110, TP8115, TP8120, TP8135, TP8140, TP7110   |

Call us now to find out more **0121 552 0067**  
 or email the sales team: [shopbleeperltd@aol.com](mailto:shopbleeperltd@aol.com)